

Product Code

F07440

## SKYLINE PROXIMITY READER V



Reference

7440

EAN

8424299074405

## Description.

## Description

- Reader that allows the door to be opened by bringing a proximity card or key fob closer to it. Only authorized cards or key fobs will operate the device. No physical contact is necessary.
- Proximity reader that, through a configuration of dials (SW2) that it incorporates, can operate in an autonomous or centralized system.

## Configuration as AUTONOMOUS.

- Capacity for up to 400 user cards or keychains.
- Reader and controller integrated in the same module.

## Configuration as CENTRALIZED MDS-AC Plus.

- Proximity reader with capacity of up to:
  - 1020 user cards/keychains with the MDS central unit (ref. 2405).
  - 2048 user cards/keychains with the AC Plus central unit (ref. 4410).
- Reader and controller integrated in the same module.

## Configuration as CENTRALIZED with Wiegand 26 or Data/Clock protocol.

- When starting the reader if it is in mode:
  - Wiegand-26, the "+" LED will light up for 1 second.
  - Data/Clock, the "-" LED will light up for 1 second.
- Proximity reader with capacity of up to:

- 1020 user cards/keychains with the MDS central unit (ref. 2405).
- 2048 user cards/keychains with the AC Plus central unit (ref. 4410).
- Requires a door controller (ref. 4420) for connection and operation.
- Acoustic and visual confirmation through LEDs signaling the acceptance or rejection of the card presented.
- Access control module, to be incorporated into SKYLINE and CITYLINE intercom/video intercom panels.
- Recommended for indoors and outdoors.

#### Technical Details

##### **AUTONOMOUS Technical Features:**

- Does not require physical reader-card contact. Reading distance at 5 cm (card) or 1.5 cm (keychain).
- Acoustic and visual information of actions.
- Manual or PC programming (card registration/deletion) is very simple.
- Door sensor control and exit button
- Relay output.
- Door release activation by relay with programmable time. Programmable 1 to 99 sec.
- Signaling LEDs (help with programming and status).

##### **Autonomous Programming** - It can be done in 3 ways:

- By Master Card.
- Private programming keyboard.
- PC software.

##### **MDS-AC Plus CENTRALIZED Technical Characteristics:** -

It does not require physical reader-card contact. Reading distance at 5 cm (card) or 1.5 cm (keychain). - Acoustic and visual information of actions.

- Door opener button input, door sensor input and door opener relay (C, NO, NC, potential free).
- Reader Wiring – Central Unit: 2 wires (power supply) + shielded twisted pair (data). In an installation with several readers they can be connected in cascade.
- It has a dipswitch (SW1) to configure:
  - Door Number (switches 1..5): the access/door number (0..31).
  - Switch 6: No function.
  - Door release opening (switches 7..8): depending on the installation:
- Door release opening time (sec.) in MDS.
- In AC Plus software configuration (switches without function).
- Connector CN3: Keyboard connector.
- The door openers can be connected directly to the reader and for maximum security installations use the relay decoder.

**Centralized Programming** Programming is carried out from the PC software corresponding to the installed central unit (ref. 2405 or

ref. 4410).

**CENTRALIZED Technical Characteristics with Wiegand 26 or Data/Clock protocol:**

- It does not require physical reader-card contact. Reading distance at 5 cm (card) or 1.5 cm (keychain).
- Acoustic and visual information of actions.
- Wiegand (WG) or Data/Clock readers allow the installation to be provided with greater anti-sabotage security by not connecting the door opening mechanism or the exit button connection to the reader. All devices are connected to the door controller and are therefore out of reach of manipulation. The door controller will be installed inside (safe zone) and the reader outside.
- The reader can be used with other door controllers that use the Wiegand 26 (WG) or Data/Clock protocols.
- Wiring: 7 wires to the door controller.
- For more information, see Technical Characteristics of the door controller.

**Centralized Programming** Programming is carried out from the PC software corresponding to the installed central unit (ref. 2405 or ref. 4410).

**Specifications** Dimensions V (HxV mm): 105.2 x 47.5 Environmental protection (IP): 52 Shock protection (IK): 07 Power supply (V): Autonomous: 12V (ac/dc). Centralized: 12Vdc Consumption (mA) without lock release: 90 Operating temperature: -15 to 55°C

Details.

Product measurements (height x width x depth) mm	Weight (kg)	Packaging measurements (height x width x depth) cm	Video Door Entry system Technologie
105 x 48	0.239168	13,5x10x6	GENERICA

Access Control Technology

PROXIMIDAD

Manuals

- 970112\_Normativa\_Modulo\_radiofrecuencia\_V10\_17.pdf
- 97597Ac Lector Proximidad Autonomo NCity V09\_16.pdf
- 97597Ec Lector Proximidad Autonomo NCity V09\_16.pdf
- 97597Fc Lector Proximidad Autonomo NCity V09\_16.pdf
- 97597Ic\_Lector\_Proximidad\_Autonomo\_NCity\_V09\_16.pdf
- 97597Pc Lector Proximidad Autonomo NCity V09\_16.pdf
- 97598c\_Lector\_Proximidad\_Centralizado\_NCity\_V09\_16.pdf

## Declaration of conformity

- [DOCF07440EN.pdf](#)

## Accessories



F02306

MANUAL PROGRAMING KEYPAD



F02336

PROXIMITY CARD EM (WITH  
MAGNETIC STRIPE)



F23361

PROXIMITY CARD W/O MAGNETIC  
STRIP EM



F04515

PROXIMITY KEYRING EM